



**Note:** This API call is for DOS and Win16 personality only. Use [Family API](#) for portability.

2018/09/07 05:04 · prokushev · [0 Comments](#)

# Int 21H, AH=57H, AL=00H

## Version

2 and higher

## Brief

GET FILE'S LAST-WRITTEN DATE AND TIME

## Family API

## Input

```
AX = 5700h  
BX = file handle
```

## Return

CF clear if successful

```
CX = file's time (see #01665)  
DX = file's date (see #01666)  
CF set on error  
AX = error code (01h,06h) (see #01680)
```

## Notes

under DR DOS 3.41 and 5.0, this function returns 0 (no date/time) for character devices; MS-DOS returns date and time of opening

Bitfields for file time:

| Bit(s) | Description  |
|--------|--------------|
| 15-11  | hours (0-23) |
| 10-5   | minutes      |
| 4-0    | seconds/2    |

Bitfields for file date:

| Bit(s) | Description |
|--------|-------------|
| 15-9   | year - 1980 |
| 8-5    | month       |
| 4-0    | day         |

AX=[5701h](#),AX=[5704h](#)“Windows95”

Note

Text based on [Ralf Brown Interrupt List Release 61](#)

| DOS API              |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|----------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Process manager      | <a href="#">INT 20H</a> , <a href="#">INT 21H</a> : <a href="#">00H</a> , <a href="#">25H</a> , <a href="#">26H</a> , <a href="#">31H</a> , <a href="#">34H</a> , <a href="#">35H</a> , <a href="#">4BH</a> , <a href="#">4CH</a> , <a href="#">4DH</a> , <a href="#">50H</a> , <a href="#">51H</a> , <a href="#">52H</a> , <a href="#">55H</a> , <a href="#">62H</a> , <a href="#">INT 22H</a> , <a href="#">INT 27H</a> , <a href="#">INT 28H</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| File manager         | <a href="#">INT 25H</a> , <a href="#">INT 26H</a> , <a href="#">INT 21H</a> : <a href="#">0DH</a> , <a href="#">0EH</a> , <a href="#">0FH</a> , <a href="#">10H</a> , <a href="#">11H</a> , <a href="#">12H</a> , <a href="#">13H</a> , <a href="#">14H</a> , <a href="#">15H</a> , <a href="#">16H</a> , <a href="#">17H</a> , <a href="#">19H</a> , <a href="#">1AH</a> , <a href="#">1BH</a> , <a href="#">1CH</a> , <a href="#">21H</a> , <a href="#">22H</a> , <a href="#">23H</a> , <a href="#">24H</a> , <a href="#">27H</a> , <a href="#">28H</a> , <a href="#">29H</a> , <a href="#">2EH</a> , <a href="#">2FH</a> , <a href="#">32H</a> , <a href="#">3305H</a> , <a href="#">36H</a> , <a href="#">39H</a> , <a href="#">3AH</a> , <a href="#">3BH</a> , <a href="#">3CH</a> , <a href="#">3DH</a> , <a href="#">3EH</a> , <a href="#">3FH</a> , <a href="#">40H</a> , <a href="#">41H</a> , <a href="#">42H</a> , <a href="#">4300H</a> , <a href="#">4301H</a> , <a href="#">45H</a> , <a href="#">45H</a> , <a href="#">46H</a> , <a href="#">4EH</a> , <a href="#">4FH</a> , <a href="#">54H</a> , <a href="#">56H</a> , <a href="#">5700H</a> , <a href="#">5701H</a> , <a href="#">5AH</a> , <a href="#">5BH</a> , <a href="#">5c00H</a> , <a href="#">5c01H</a> , <a href="#">60H</a> , <a href="#">67H</a> , <a href="#">68H</a> , <a href="#">6900H</a> , <a href="#">6901H</a> , <a href="#">6AH</a> , <a href="#">6CH</a> |
| Character Device I/O | <a href="#">INT 29H</a> , <a href="#">INT 21H</a> : <a href="#">01H</a> , <a href="#">02H</a> , <a href="#">03H</a> , <a href="#">04H</a> , <a href="#">05H</a> , <a href="#">06H</a> , <a href="#">07H</a> , <a href="#">08H</a> , <a href="#">09H</a> , <a href="#">0AH</a> , <a href="#">0BH</a> , <a href="#">0AH</a> , <a href="#">0CH</a> , <a href="#">5D07H</a> , <a href="#">5D08H</a> , <a href="#">5D09H</a> , <a href="#">5D0AH</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| Signals              | <a href="#">INT 23H</a> , <a href="#">INT 24H</a> , <a href="#">INT 21H</a> : <a href="#">3300H</a> , <a href="#">3301H</a> , <a href="#">3302H</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| Memory manager       | <a href="#">INT 21H</a> : <a href="#">48H</a> , <a href="#">49H</a> , <a href="#">4AH</a> , <a href="#">5800H</a> , <a href="#">5801H</a> , <a href="#">5802H</a> , <a href="#">5803H</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| Date and Time        | <a href="#">INT 21H</a> : <a href="#">2AH</a> , <a href="#">2BH</a> , <a href="#">2CH</a> , <a href="#">2DH</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| Misc                 | <a href="#">INT 21H</a> : <a href="#">30H</a> , <a href="#">3306H</a> , <a href="#">3700H</a> , <a href="#">3701H</a> , <a href="#">3702H</a> , <a href="#">3703H</a> , <a href="#">59H</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| NLS                  | <a href="#">INT 21H</a> : <a href="#">3303H</a> , <a href="#">3304H</a> , <a href="#">3800H</a> , <a href="#">3801H</a> , <a href="#">6300H</a> , <a href="#">6301H</a> , <a href="#">6301H</a> , <a href="#">6500H</a> , <a href="#">6501H</a> , <a href="#">6502H</a> , <a href="#">6503H</a> , <a href="#">6504H</a> , <a href="#">6505H</a> , <a href="#">6506H</a> , <a href="#">6507H</a> , <a href="#">6520H</a> , <a href="#">6521H</a> , <a href="#">6522H</a> , <a href="#">6523H</a> , <a href="#">65A0H</a> , <a href="#">65A1H</a> , <a href="#">65A2H</a> , <a href="#">6601H</a> , <a href="#">6602H</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
| Devices              | <a href="#">INT 21H</a> : <a href="#">4400H</a> , <a href="#">4401H</a> , <a href="#">4402H</a> , <a href="#">4403H</a> , <a href="#">4404H</a> , <a href="#">4405H</a> , <a href="#">4406H</a> , <a href="#">4407H</a> , <a href="#">4408H</a> , <a href="#">4409H</a> , <a href="#">440AH</a> , <a href="#">440BH</a> , <a href="#">440CH</a> , <a href="#">440DH</a> , <a href="#">440EH</a> , <a href="#">440FH</a> , <a href="#">4410H</a> , <a href="#">4411H</a> , <a href="#">53H</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
| Network              | <a href="#">INT 21H</a> : <a href="#">5E00H</a> , <a href="#">5E01H</a> , <a href="#">5E02H</a> , <a href="#">5E03H</a> , <a href="#">5E04H</a> , <a href="#">5E05H</a> , <a href="#">5F00H</a> , <a href="#">5F01H</a> , <a href="#">5F02H</a> , <a href="#">5F03H</a> , <a href="#">5F04H</a> , <a href="#">5F05H</a> , <a href="#">5F07H</a> , <a href="#">5F08H</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
| osFree Macro Library |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| Video I/O            | <a href="#">@SetMode</a> <a href="#">@SetCurSz</a> <a href="#">@SetCurPos</a> <a href="#">@GetCur</a> <a href="#">@SetPage</a> <a href="#">@ScrollUp</a> <a href="#">@ScrollDn</a> <a href="#">@Scroll</a> <a href="#">@GetChAtr</a> <a href="#">@PutChAtr</a> <a href="#">@PutCh</a> <a href="#">@SetPalet</a> <a href="#">@SetColor</a> <a href="#">@SetDot</a> <a href="#">@GetDot</a> <a href="#">@WrtTTY</a> <a href="#">@VideoState</a> <a href="#">@GetMode</a> <a href="#">@GetDisplay</a> <a href="#">@GetVideoState</a> <a href="#">@GetEGAInfo</a> <a href="#">@Cls</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| Hardware info        | <a href="#">@Equipment</a> <a href="#">@MemSize</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| Serial I/O           | <a href="#">@AuxInit</a> <a href="#">@AuxSendChar</a> <a href="#">@AuxRecieveChar</a> <a href="#">@AuxStatus</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| Tape I/O             | <a href="#">@TapeOn</a> <a href="#">@TapeOff</a> <a href="#">@TapeRead</a> <a href="#">@TapeWrite</a>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |

**osFree Macro Library**

|                |                                                                         |
|----------------|-------------------------------------------------------------------------|
| Keyboard I/O   | @KbdStatus @CharIn @CharPeek                                            |
| Printer I/O    | @PrnPrint @PrnInit @PrnStatus                                           |
| Disk I/O       | @DskReset @DskStatus @DskRead @DskWrite @DskVerify @DskFormat           |
| Date and Time  | @SetTime @GetTime                                                       |
| Mouse          | @MouInit @MouShowPointer @MouStatus @MouSetPos @MouSetMickey @MouRegion |
| Memory manager | @ModBlok SET_BLOCK                                                      |

2022/10/04 14:28 · prokushev · 0 Comments

2018/09/04 17:23 · prokushev · 0 Comments

**Family API**

|           |                 |                                                                                                                                                                                                                                                                                                                                                                              |
|-----------|-----------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| DOS       | Process Manager | DosBeep DosExit DosSleep DosExecPgm                                                                                                                                                                                                                                                                                                                                          |
|           | File Manager    | DosChDir DosChgFilePtr DosClose DosDelete DosDupHandle DosMkDir DosMove DosQCurDir DosQCurDisk DosSetFileMode DosOpen DosQFileInfo DosRead DosQFileMode DosQFSInfo DosQVerify DosRmdir DosSelectDisk DosFindClose DosFindFirst DosFindNext DosSetFileInfo DosSetVerify DosWrite DosFileLocks DosSetFHandState DosNewSize DosBufReset DosQFHandState DosSetFSinfo DosShutdown |
|           | Memory Manager  | DosFreeSeg DosSubAlloc DosSubFree DosSubSet DosAllocHuge DosAllocSeg DosReallocHuge DosReallocSeg DosGetHugeShift DosCreateCSAlias                                                                                                                                                                                                                                           |
|           | NLS             | DosCaseMap DosGetCtryInfo DosGetDBCSEv DosSetCtryCode DosGetCollate DosGetMessage DosInsMessage DosPutMessage                                                                                                                                                                                                                                                                |
|           | Date and Time   | DosSetDateTime DosGetDateTime                                                                                                                                                                                                                                                                                                                                                |
|           | Devices         | DosDevConfig DosDevIOctl DosDevIOctl2                                                                                                                                                                                                                                                                                                                                        |
|           | Signals         | DosHoldSignal DosSetSigHandler                                                                                                                                                                                                                                                                                                                                               |
|           | Misc            | BadDynLink DosGetEnv DosGetMachineMode DosGetVersion DosError DosErrClass DosSetVec                                                                                                                                                                                                                                                                                          |
| KBD       |                 | KbdCharIn KbdFlushBuffer KbdGetStatus KbdSetStatus KbdStringIn KbdPeek                                                                                                                                                                                                                                                                                                       |
| VIO       |                 | VioGetBuf VioGetConfig VioGetCurPos VioGetCurType VioGetPhysBuf VioReadCellStr VioReadCharStr VioScrollUp VioScrollDn VioScrollLf VioScrollRt VioScrUnLock VioSetCurPos VioSetCurType VioSetMode VioGetMode VioShowBuf VioWrtCellStr VioWrtCharStr VioWrtCharStrAtt VioWrtNAttr VioWrtNCell VioWrtNChar VioWrtTTY VioScrLock VioPopUp                                        |
| Tools     |                 | BIND                                                                                                                                                                                                                                                                                                                                                                         |
| Modules   |                 | DOSCALLS.DLL VIOCALLS.DLL KBDCALLS.DLL MSG.DLL                                                                                                                                                                                                                                                                                                                               |
| Libraries |                 | API.LIB OS2386.LIB FAPI.LIB DOSCALLS.LIB SUBCALLS.LIB                                                                                                                                                                                                                                                                                                                        |

2018/08/25 15:05 · prokushev · 0 Comments

From:

<http://www.osfree.org/doku/> - **osFree wiki**

Permanent link:

<http://www.osfree.org/doku/doku.php?id=en:docs:dos:api:int21:57:00>Last update: **2024/05/03 03:53**