



**Note: This API calls are shared between DOS and Win16 personality.**

DPMI is a shared interface for DOS applications to access Intel 80286+ CPUs services. DOS DMPI host provides core services for protected mode applications. Multitasking OS with DOS support also provides DMPI in most cases. Windows standard and extended mode kernel is a DPMI client app. Standard and extended mode kernel differs minimally and shares common codebase. Standard Windows kernel works under DOSX extender. DOSX is a specialized version of 16-bit DPMI Extender (but it is standard DPMI host). Standard mode is just DPMI client, enhanced mode is DPMI client running under Virtual Machine Manager (really, multitasker which allow to run many DOS sessions). Both modes shares DPMI interface for kernel communication. The OS/2 virtual DOS Protected Mode Interface (VDPMI) device driver provides Version 0.9 DPMI support for virtual DOS machines. Win16 (up to Windows ME) provides Version 0.9 DPMI support. Windows in Standard Mode provides DPMI services only for Windows Applications, not DOS sessions.

DPMI host often merged with DPMI extender. Usually DPMI extender provide DPMI host standard services and DOS translation or True DPMI services.

2021/08/05 10:15 · prokushev · [0 Comments](#)

## Int 31H, AH=0BH, AL=02H

### Version

0.9

### Brief

Get State of Debug Watchpoint

### Input

```
AX = 0B02H
BX = watchpoint handle
```

### Return

```
if function successful
Carry flag = clear
AX = watchpoint status
```

Bit	Significance
0	0 = watchpoint has not been encountered 1 = watchpoint has been encountered
1-15	reserved

## Notes

Returns the state of a debug watchpoint that was previously set using the Set Debug Watchpoint function (Int 31H Function 0B00H).

The client can use Int 31H Function 0B03H to clear the watchpoint state without releasing the watchpoint handle.

## See also

## Note

Text based on <http://www.delorie.com/djgpp/doc/dpmi/>

DPMI	
Process manager	<a href="#">INT 2FH 1680H, 1687H</a>
Signals	
Memory manager	
Misc	<a href="#">INT 2FH 1686H, 168AH</a>
Devices	

2021/08/13 14:23 · prokushev · [0 Comments](#)

From:  
<https://cocorico.osfree.org/doku/> - **osFree wiki**

Permanent link:  
<https://cocorico.osfree.org/doku/doku.php?id=en:docs:dpmi:api:int31:0b:02>

Last update: **2021/08/27 06:29**

