



Note: This IBM PC BIOS API call is for DOS/Win16 personality only. Use [Family API](#) for portability.

Note: [osFree Macro Library](#) provides macros for most of functions

2022/03/13 05:41 · prokushev · [0 Comments](#)

@AuxRecieveChar

Brief

Recieve char from serial port

BIOS Interrupt

[INTH: H](#)

Family API

[fapi](#)

Syntax

@AuxRecieveChar

Parameters

none

Return

- AL = received character if AH bit 7 clear
- AH bit 7 clear if successful
- AH bit 7 set on error
- AH bits 6-0 = port status:

Bit(s)	Description
7	timeout
6	transmit shift register empty
5	transmit holding register empty
4	break detected
3	framing error
2	parity error
1	overrun error
0	receive data ready

From:

<https://www.osfree.org/doku/> - **osFree wiki**

Permanent link:

<https://www.osfree.org/doku/doku.php?id=en:docs:macrolib:auxrecievechar>

Last update: **2022/10/02 03:31**

